

## Bluetooth Contactless reader



- ✓ **NFC TAG reader (T1T/T2T/T3T/T4T)**
- ✓ **Mifare Series, FeliCa**
- ✓ **S D K for Windows & Android**
- ✓ **Bluetooth wireless communication**

### Applications

- Transportation: Contactless / NFC ticket management
- e-Purse & Loyalty : In-store coupon/loyalty management, Local payment
- Event /Festival visitor management

# DRAGON BT

Wireless contactless reader



## Specifications

<b>CPU</b>	ARM 32-bit CPU
<b>Program / Data Memory</b>	128KBytes Flash / 20KBytes SRAM
<b>Host Interface</b>	Bluetooth v.2.1 + EDR Micro USB (Recharge & Communication)
<b>Contactless Communication</b>	ISO 14443 A/B, Mifare, DESFire, FeliCa, ISO15693 ISO 18092 4 tag type
<b>Contact Communication</b>	ISO 7816 compliant (SAM X 1EA)
<b>Reading Distance</b>	Maximum 5cm
<b>User Interface</b>	4 Status LED ( POWER, BLUETOOTH, RF, BATTERY ) Vibrator Buzzer
<b>Battery</b>	620mAh (5~6hours operation/ 14hours stand-by mode) Sleep mode (Awake button) Re-chargeable via micro USB cable
<b>Dimension / Weight</b>	60 X 103 X 11.5mm/ 47.5g
<b>Operating Temperature</b>	-10 ~ 60 °C

**Kimaldi Electronics, S.L.**

Ctra. de Rubí, 292 B - Pol.  
Ind. Can Guitard - Sector La  
Constancia  
08228 - Terrassa  
(Barcelona) Spain  
Telèfon: +34 93 736 15 10  
Fax: +34 93 736 15 11  
E-mail:  
kimaldi@kimaldi.com

**Kimaldi Lusa**

EN 247, KM 64,5  
Park Charal, Armazém 4  
Carne Assada  
2705-837 Terrugem -  
Portugal  
Tel: +351 21 715 63 03  
Fax: +351 21 715 62 95  
E-mail:  
portugal@kimaldi.com